



SINGE PHASE 0.8AMP GLASS PASSIVATED BRIDGE RECTIFIERS

Voltage

600~1000 V

Current


0.8 A

Features

- Ideal for printed circuit board
 Reliable low cost construction utilizing
 molded plastic technique results in inexpensive product
- High surge current capability
- Small size simple installation
- Lead free in compliance with EU RoHS 2011/65/EU directive.

Mechanical Data

- Case: MBS Molded plastic
- Terminals: Solder plated, solderable per MIL-STD-750, Method 2026
- Polarity: As marking
- Approx weight: 0.0042 ounce, 0.12 gram



Maximum Ratings (T_A=25°C unless otherwise noted)


PARAMETER		SYMBOL	MB6S-08	MB8S-08	MB10S-08	UNIT
Maximum repetitive peak reverse voltage		V_{RRM}	600	800	1000	V
Maximum rms voltage		V_{RMS}	420	560	700	٧
Maximum dc blocking voltage		V_{R}	600	800	1000	V
Maximum average forward current per diode		I _{F(AV)}	0.8		Α	
Peak forward surge current : 8.3ms single half sine wave superimposed on rated load per diode	-	I _{FSM}	30		Α	
Maximum forward voltage at 0.8A per diode		V_{F}	1.1		V	
Maximum dc reverse current at rated dc blocking voltage per diode		I _R	5		μΑ	
Typical junction capacitance Measured at 1MHz and applied V _R =4V		СJ		9		pF
Typical thermal resistance per diode	(Note 1) (Note 2) (Note 2)	$egin{array}{c} {\sf R}_{ heta {\sf JA}} \ {\sf R}_{ heta {\sf JC}} \ {\sf R}_{ heta {\sf JL}} \end{array}$	85 14 20		°C/W	
Operating junction temperature		T_J	-55 to +150		°C	
Storage temperature		T_{STG}	-55 to +150		°C	


Note: 1. Mounted on a FR4 PCB, single-sided copper, mini pad.


2. Mounted on a FR4 PCB with 100cm² copper pad area.



















PART NO PACKING CODE VERSION

Part No Packing Code	Package Type	Packing Type	Marking	Version
MB6S-08_R2_00001	MBS	3K pcs / 13" reel	MB608	Halogen free
MB8S-08_R2_00001	MBS	3K pcs / 13" reel	MB808	Halogen free
MB10S-08_R2_00001	MBS	3K pcs / 13" reel	MB1008	Halogen free

MOUNTING PAD LAYOUT







Disclaimer

- Reproducing and modifying information of the document is prohibited without permission from Panjit International Inc..
- Panjit International Inc. reserves the rights to make changes of the content herein the document anytime without notification. Please refer to our website for the latest document.
- Panjit International Inc. disclaims any and all liability arising out of the application or use of any product including damages incidentally and consequentially occurred.
- Panjit International Inc. does not assume any and all implied warranties, including warranties of fitness for particular purpose, non-infringement and merchantability.
- Applications shown on the herein document are examples of standard use and operation. Customers
 are responsible in comprehending the suitable use in particular applications. Panjit International Inc.
 makes no representation or warranty that such applications will be suitable for the specified use
 without further testing or modification.
- The products shown herein are not designed and authorized for equipments requiring high level of reliability or relating to human life and for any applications concerning life-saving or life-sustaining, such as medical instruments, transportation equipment, aerospace machinery et cetera. Customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Panjit International Inc. for any damages resulting from such improper use or sale.
- Since Panjit uses lot number as the tracking base, please provide the lot number for tracking when complaining.